

APPLICATION FOR UNITED STATES LETTERS PATENT

for

SCENE CHANGE DETECTION

Inventors:
Ming-Chang Liu
Wei-Jen Li
Ikuo Tsukagoshi

Prepared by:

BLAKELY SOKOLOFF TAYLOR & ZAFMAN LLP
12400 Wilshire Boulevard
Los Angeles, CA 90025-1026
(408) 720-8598

Attorney Docket No.: 80398.P465

"Express Mail" mailing label number: EL867652663US

Date of Deposit: December 11, 2001

I hereby certify that I am causing this paper or fee to be deposited with the United States Postal Service "Express Mail Post Office to Addressee" service on the date indicated above and that this paper or fee has been addressed to the Commissioner for Patents, Washington, D. C. 20231

Sheryl Sue Holloway
(Typed or printed name of person mailing paper or fee)

[Signature]
(Signature of person mailing paper or fee)

12/11/01
(Date signed)

SCENE CHANGE DETECTION

RELATED APPLICATIONS

[0001] The present application claims the benefit of U.S. provisional patent applications serial nos. 60/254,804, 60/254,953 and 60/254,809, all filed on December 11, 2000.

FIELD OF THE INVENTION

[0002] The present invention relates to devices and methods for efficiently encoding digital video.

RELATED ART

[0003] One type of film runs at 24 Hz. That is, twenty four frames of film are displayed every second. In the United States, according to the National Television System Committee (NTSC) standards, television video runs at 30 Hz. When converting film to be shown on television, problems arise because of the extra frames needed for every second of television broadcast. More specifically, there are six more frames of television video every second than corresponding film frames, and in order to display film on television with proper timing something must be done to fill in the last six frames. Further, according to the NTSC standard, television video is interlaced. That is, every frame is further made up of two fields, a top field and a bottom field. So, for every second, 60 fields of video are shown.

[0004] In order to solve the problem of having extra video frames when converting film to be shown on television, the 3:2 pull down process converts two frames of film into five fields of video. One method of performing this process involves repeating one of the fields. More specifically, this method involves converting the two frames of film into two frames of video, each frame of video having two fields, and then repeating one of the video fields to correct the timing.

[0005] Digitally encoded video is typically compressed because video can require an enormous amount of digital storage if left uncompressed. One method for compressing digital video involves using the standards of the Moving Pictures Experts Group (MPEG). The MPEG-2 standard calls for three types of frames to be encoded. Intra-

frames, or I-frames are encoded in the same manner as still images; an I-frame contains information sufficient to display an entire image. Predictive frames, or P-frames use previous reference frames to determine what the current frame will be by recording changes between a previous frame and the current frame. Bi-directional frames, or B-frames use previous and subsequent reference frames to determine what the current frame will be. P-frames and B-frames use motion vectors to encode frames.

[0006] A motion vector determines movement between specific areas of one frame to another frame. For example, a P-frame may be encoded by referencing an I-frame immediately preceding it. Motion vectors between the P-frame and the I-frame instruct a decoder to display the P-frame by using motion vectors to determine movement of certain areas within the I-frame which results in the proper display of the P-frame.

[0007] More specifically, each frame can be divided up into a number of macroblocks. A macroblock is a group of pixels; for example a macroblock could be a square 16 pixels by 16 pixels. A motion vector can then record the movement of a macroblock in a first frame to its new position in a second frame. For example, a macroblock in a first frame could be a black 16 by 16 pixel square in the lower left hand corner. In the second frame, the black square may move to the upper right hand corner of the frame. Instead of recording the characteristics of the black square in the second frame, the second frame can instead have a motion vector indicating that the black square, which was in the lower left hand corner in the first frame, has moved to the upper right hand corner in the second frame. Since a macroblock will generally contain much more data information than a motion vector which indicates the direction of movement of a previously encoded macroblock, motion vectors can greatly reduce the amount of data necessary for digital video.

[0008] One method of encoding digital video calls for grouping frames together into what are known as Groups of Pictures (GOPs). A GOP may begin with an I-frame, and have P-frames and B-frames which refer to the I frame. A P-frame or a B-frame can refer to either an I-frame or a P-frame, but not to a B-frame. The length and order of GOPs can be determined before encoding or dynamically, while the encoder is encoding. An example of a sequence of a GOP may be IBBPBBPBB, meaning an I-frame, followed by two B frames, a P frame, two more B-frames, another P-frame, two more B-frames, and an I-frame. In an encoder which determines the order of a GOP prior to

encoding, this sequence would repeat itself. In the above sequence, the first P-frame will refer back to the first I-frame, since it cannot refer to a B-frame, and must refer to a frame that occurs before it. The B-frames may refer to any of the I- or P-frames.

[0009] One method of applying 3:2 pull down introduces a repeated field for every five fields of video. When encoding video, which at one time was film, the 3:2 pull down process leaves a repeated field as one out of every five fields. This repeated field can be detected and removed. By removing repeated fields, the encoding process can be made more efficient, and ultimately the amount of the resulting data can be greatly reduced. However, current methods for detecting repeated fields, such as pixel to pixel matching from field to field, can require too much processing time and too many resources. Therefore, an efficient and effective method for determining which fields are repeated is needed.

[0010] Further, it is advantageous for the encoder to be able to detect when a new scene is beginning in a video sequence. Current methods for detecting a scene change include histogram-based algorithms and block matching algorithms. These methods are very processor intensive, and generally cannot be used for real-time digital video encoding. Therefore, an efficient and effective method for detecting scene changes during digital video encoding is needed.

SUMMARY OF THE INVENTION

[0011] In one embodiment, a scene change detection component of a video encoder uses motion vectors to determine whether a scene change occurs in a video sequence. The scene change detection component uses field motion vectors determined by a motion estimator and compares the field motion vectors to a threshold to determine whether a scene change occurs. In another embodiment, if a scene change occurs, the video encoder can begin a new Group of Pictures (GOP).

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217

BRIEF DESCRIPTION OF THE DRAWINGS

- [0012] Figure 1 is a flow diagram illustrating the process of a video encoder according to one embodiment.
- [0013] Figure 2 illustrates a system for encoding and decoding digital video according to one embodiment.
- [0014] Figure 3a illustrates a video encoder and associated hardware, according to one embodiment.
- [0015] Figure 3b illustrates an encoder according to one embodiment.
- [0016] Figure 4 is a timing diagram for a video sequence without scene change or repeated fields.
- [0017] Figure 5 is a timing diagram for a video sequence with repeated fields.
- [0018] Figure 6 is a timing diagram for a video sequence with an I-frame in between two repeated fields.
- [0019] Figure 7 is a timing diagram for a video sequence with a scene change during a top-field-first situation.
- [0020] Figure 8 is a timing diagram for a video sequence with a scene change during a bottom-field-first situation.
- [0021] Figure 9 is a flow diagram illustrating the operation of an encoder according to one embodiment.
- [0022] Figure 10 illustrates a video sequence having a scene at a B-frame (immediate) right after an I-frame.
- [0023] Figure 11 illustrates a video sequence having a scene change occurring two frames after an I-frame.
- [0024] Figure 12 illustrates a video sequence having a scene change happening at a B-frame.
- [0025] Figure 13 illustrates a video sequence having a scene change occurring at a P-frame.
- [0026] Figure 14 illustrates a video sequence having a repeated field in an I-frame.
- [0027] Figure 15 illustrates a video sequence having a repeated field in a B-frame.
- [0028] Figure 16 illustrates a video sequence having a repeated field in a P-frame.
- [0029] Figures 17a, 17b, 17c are block diagrams of an encoder according to one embodiment.

[0030] Figure 18a illustrates two video frames and their associated motion vectors according to one embodiment.

[0031] Figure 18b illustrates a sequence of frames operating in a top-field-first condition.

[0032] Figure 18c illustrates a sequence of frames with a repeated field in a top-field-first condition.

[0033] Figure 18d illustrates a sequence of frames operating in a bottom-field-first condition.

[0034] Figure 18e illustrates a sequence of frames with a repeated field in a bottom-field-first condition.

[0035] Figures 19a, 19b, 19c, 19d, 19e, and 19f illustrate a sequence of frames having repeated fields according to one embodiment.

[0036] Figure 20 illustrates two frames and their associated motion vectors according to one embodiment.

[0037] Figure 21 is a flow diagram illustrating the process of detecting repeated fields according to one embodiment.

[0038] Figures 22a, 22b, and 22c illustrate a sequence of frames containing a scene change according to one embodiment.

[0039] Figure 22d illustrates an interlaced video sequence having a scene change.

[0040] Figure 22e illustrates a progressive video sequence having a scene change.

[0041] Figure 23 illustrates two frames and their associated motion vectors according to one embodiment.

[0042] Figure 24 is a flow diagram illustrating the process of detecting repeated fields according to one embodiment.

DETAILED DESCRIPTION

[0043] The present invention relates to devices and methods for efficiently encoding digital video. This invention may be used to increase efficiency when encoding video that has been processed using a 3:2 pull down process. Although the embodiments described below relate to encoding video that has been processed using a 3:2 pull down process, it is understood that the present invention may be used for any type of video.

[0044] Figure 1 is a flow diagram illustrating the process of a video encoder according to one embodiment. The encoder accepts a video sequence as an input, and outputs a digitally encoded video bitstream. According to one embodiment, the video encoder encodes video according to an MPEG standard. The process illustrated in Figure 1 is generally described; more detail will be added in figures following. It is understood that while the process of Figure 1 illustrates one embodiment of the invention, there are numerous methods of encoding video, and one skilled in the art will realize that the features of Figure 1 can be integrated into any number of different encoders.

[0045] At block 105, pre-filtered output is inputted into the video encoder. The pre-filtered output of block 105 is first sent to phase of a motion estimator in block 110. A motion estimator, which determines motion vectors to encode frames, is here split into two separate phases. Phase one of the motion estimator entails determining two sets of motion vectors, one set between the first field of a first frame and the first field of a second frame and another set between a second field of a first frame and a second field of a second frame. The second phase of the motion estimator determines the remaining motion vectors: those between the first field of the first frame and the second field of the second frame, those between the second field of the first frame and the first field of the second frame, and those between the first frame and the second frame. The motion vectors indicate motion of macroblocks between two different frames. In a standard interlaced video sequence in which one top field and one bottom field comprise a frame, the first phase of the motion estimator determines motion vectors between fields of the same polarity. That is, two top fields are said to have the same polarity, but a top field and a bottom field are said to have opposite polarity. The motion vectors between fields of the same polarity are also known as field motion vectors.

[0046] By bifurcating the motion estimation phase, the field motion vectors may be used in the scene change detection and 3:2 pull-down detection phases in blocks 115 and 120, respectively. The field motion vectors can be used during scene change detection and 3:2 pull-down detection to generate additional information for these detections such as histograms and fields difference calculations, rather than using more processor intensive methods. Because it is necessary to determine field motion vectors for each frame in order to encode the frame, using the field motion vectors to perform the detections may introduce little extra processing into the system. It may also be advantageous to bifurcate the motion estimation phase because the result of the detections may render the second phase of the motion estimation phase unnecessary, and if the second phase is found to be unnecessary, the encoder can forgo estimating of the remaining motion vectors, saving further processing resources.

[0047] Previous video encoders had to encode I- and P-frames before B-frames were encoded because a B-frame uses I- and P-frames as references, and can reference to a frame in the future. However, using a two phase motion estimation, an encoder can encode frames using the input sequence of frames.

[0048] At block 115, a scene change detection is executed. Scene change detection uses the field motion vectors found in block 110 to determine whether the scene has changed between two frames. Generally, if there is no scene change between frames, one can expect the motion vectors of a frame to be similar to the motion vectors of the frame before it. However, if there is a scene change between frames, the motion vectors will become unpredictable and erratic. By comparing these motion vectors, it can be determined that there has been a scene change. One embodiment of a scene change detection process will be explained in more detail below.

[0049] If a scene change is detected, the encoder can order the beginning of a new Group of Pictures (GOP) immediately or soon after the scene change. As explained above, whenever a scene change occurs, the first frame of the scene change will have motion vectors which are very erratic and large in magnitude. As a result, these motion vectors will not be of much use. It may therefore be advantageous to begin a new GOP with a new I-frame, so that frames at and after the scene change do not have to refer to frames in an earlier scene which may be very different. The encoder's response to the detection of a scene change will also be explained in more detail below.

[0050] If there is no scene change, the process then moves on to block 120, where 3:2 pull-down detection is executed. As explained above, the 3:2 pull-down process introduces one field out of every five that is repeated from another field. Because this repeated field is identical to another field, a processing and data storage savings can be realized by replacing the repeated field with a reference to the earlier field from which it is repeated.

[0051] The 3:2 pull-down detection process of block 120 involves using the field motion vectors determined by the first phase of the motion estimator in block 110 to determine whether there is a repeated field. Because motion vectors indicate the motion of macroblocks, if one field is repeated from another, any motion vectors between those two fields should theoretically have a magnitude of zero. In reality, there will always be some noise in any video system, but if the sum of the magnitudes of one set of field motion vectors is significantly greater than the sum of the magnitudes of the other set of field motion vectors, then the fields which are related by the smaller sum of magnitudes can be said to be repeated. For example, if the top fields in two frames are repeated, the sum of the magnitudes of the motion vectors relating the two top fields will be significantly less than the sum of the magnitudes of the motion vectors relating the bottom fields. This is explained in more detail below.

[0052] If a repeated field is found, the repeated field can be replaced by a reference to the previous field and encoding begins again by supplying new frames to the motion estimator. However, if there is no repeated field, the encoding process continues. If there is a scene change, the 3:2 pull down detection can be bypassed and the process moves on to picture heading encoding in block 125.

[0053] Once the step of block 125 is completed, the process moves on to macroblock level encoding in block 130. Macroblock level encoding, including the second phase of the motion estimator and the mode decision for the best motion vector for each macroblock, encodes a frame at macroblock basis. The second phase of the motion estimator includes determining the motion vectors between the first field of a first frame and the second field of a second frame, between the second field of a first frame and the first field of a second frame and between a first frame and a second frame. Macro-block level encoding at block 130 completes the encoding for a specific frame. Once encoding

is completed, the next frame may be entered into the encoder and the process begins again.

[0054] Significant processing time can be saved by dividing the motion estimator into two discrete phases. The first phase, determining the first two sets of motion vectors, can be performed before the scene change detection, the 3:2 pull-down detection, and the second phase of the motion estimator. The results of the first phase can determine whether there is a scene change. Once a scene change is found it is no longer necessary to execute the 3:2 pull-down detection and the second phase of motion estimation. If there is no scene change detected, the 3:2 pull-down detection will be executed. If there is a repeated field, it need not be encoded, but a reference to the field it is repeated from can be inserted. Thus, the second phase motion estimation for a repeated field does not need to be executed. The processing resources saved from not encoding repeated fields can be used for encoding other frames to improve the quality of the video. Therefore, determining the field motion vectors first and using them to find repeated fields and scene changes can significantly reduce the amount of processing required and improve quality.

[0055] Figure 2 illustrates a system for encoding and decoding digital video according to one embodiment. Film at 24 Hz 205 can be processed in a telecine 210 which performs 3:2 pull-down to create 30 Hz video. The 30 Hz video is transferred as an analog broadcast to an end user. A device, having a video code 215 may then process the 30 Hz analog broadcast. An encoder 220, takes the 30 Hz video and encodes it at 24 Hz by removing repeated fields as in the processes explained above. The video may then be stored on data source 225. Then, the 24Hz encoded video may be decoded by decoder 230 and returned to 30 Hz video by inserting the repeated fields, which may be viewed by a user.

[0056] Figure 3a depicts a processing system 300 in which one embodiment of the invention may be implemented. For one embodiment, a video encoding device may be implemented using a general processing architecture. Referring to Figure 3a, the system may include a bus 302, or other communications means for communicating information, and a central processing unit (CPU) 304 coupled to the bus for processing information. CPU 304 includes a control unit 306, an arithmetic logic unit (ALU) 308 and registers 310. CPU 304 can be used to implement the video encoder and decoder. The processing

system 300 also includes a main memory 312, which may be a random access memory (RAM) device that is coupled to the bus 302. The main memory stores information and instructions to be executed by CPU 304. Main memory 312 may also store temporary variables and other intermediate information during the execution of instructions by CPU 304. The system 300 also includes a static memory 314, for example, a read-only memory (ROM), and/or other static device that is coupled to the bus 302 for storing static information and instructions for CPU 304. It should be realized that processor executable instructions, reflective of the processes described herein may be stored in one of the memories referred to above and/or stored or transferred through some other computer readable medium.

[0057] The encoder 320 is coupled to the bus 302 and configured to encode digital video. The encoder 320 includes a motion estimator 322 having a first phase 324 and a second phase 326. The motion estimator is used to determine motion vectors. The first phase 324 of the motion estimator determines the field motion vectors as described above and below. The second phase 326 of the motion estimator determines the third, fourth, and fifth sets of motion vectors as described above and below. The encoder 320 further includes a scene change detection component 328 to detect scene changes between frames, as explained earlier and further below. Encoder 320 also includes a 3:2 pull down detection component 330 to detect whether there are repeated fields in any frames, as explained earlier and below. In one embodiment, the encoder operates in a manner as explained in the flow diagram in Figure 1.

[0058] Figure 3b illustrates an encoder 350 according to one embodiment. Frames are input at point 352 and saved into frame buffer 354 for motion estimation. The field motion vectors V 370 from phase-one motion estimator 358 are stored in field motion vector buffer 356 for scene change detector 360 and 3:2 pull-down detector 362 to use. The scene change detector 360 sends the detection outcome 372, an indicator i_{sc} , to inform encoder controller 366. The 3:2 pull-down detector 362 sends the detection outcome 374, and indicator i_{pd} , to inform the encoder controller 366 and to eliminate repeated field.

[0059] According to one embodiment, the flow of the encoder is explained above, in Figure 1. Motion estimation phase 1 358 accepts inputted frames and computes field motion vectors for the inputted frames. As explained above, the phase 1 358 only

computes the field motion vectors, which are the motion vectors between fields having the same polarity. Scene change detection component 360 uses the field motion vectors of phase 1 358 to determine whether a scene change exists. Depending on whether there is a scene change or not, the encoder may alter the encoding process, as explained below. 3:2 pull-down detection component 362 uses the field motion vectors outputted from phase 1 358 to determine whether a repeated field exists in an inputted frame. If a repeated field exists, the eliminate repeated field component 364 may eliminate the repeated field using any of several known methods, including removing the field and inserting a reference to a previous field, and averaging the two identical fields to improve the image quality.

[0060] The controller, including motion estimation phase 2 366, finalizes this encoding process. Phase 2 of the motion estimation process 366 determines the remaining motion vectors, using a reconstructed frame 368 as a reference, which refers to a reconstructed frame occurring before the frame which is being encoded. In one embodiment, the phase 1 uses frames from the original video sequence to determine motion vectors. Using original frames to compute motion vectors can lead to more accurate motion vectors because the original frames are not deteriorated. Phase 2 can use reconstructed frames because the decoder has no information about the original frames, so the phase 2 motion estimation would need to use reconstructed frames to avoid error drifting. The controller including motion estimation phase 2 366 outputs motion vectors 370.

[0061] This approach not only has effects of mixing reference to the original frames and the reconstructed frames, but greatly reduces the overall computational load, especially when repeated fields are detected. In addition, since phase-one motion estimation is separated from the encoding process, it can be executed in the same order as input frames. Thus, this two-phase motion estimation structure will not increase the complexity of the encoder.

[0062] Figures 4, 5, 6, 7, 8, and 9 illustrate timing considerations when using a motion estimator according to some embodiments. The following timing diagrams explain the operation of a motion estimator only in specific circumstances, and are meant only as examples of the operation of a motion estimator. The following diagrams may be used to explain the timing considerations of the process of Figure 1.

[0063] Motion estimation with the mode decision to determine the best motion vector for each macroblock is one of the most computation intensive processes that an encoder must complete. As a result, a processor must take timing into account when the motion estimation process is modified, for example, when a repeated field is detected and the second phase of the motion estimation becomes unnecessary. The following timing diagrams illustrate such considerations.

[0064] In one embodiment, a video encoder normally operates the top-field-first condition. That is, when using interlaced frames, each frame having a top field and a bottom field, the top field is encoded before the bottom field. In the bottom-field-first condition, the bottom field of the frame is encoded first. As explained below, it is possible for the encoder change from the top-field-first condition to the bottom-field-first condition.

[0065] Figure 4 is a timing diagram for a video sequence without scene change or repeated fields. Frames 401, 402, 403, 404, 405, 406, 407, 408, and 409 are to be encoded. Frames 401 through 409 are to be shown sequentially. Here, frame 408 is an I-frame. At time 410, the motion estimator initiates with two phase one motion estimations in order to apply 3:2 pull-down detection. This initiation puts the first phase two frames ahead of the second phase. For example, frame 404 is processed in the first phase of the motion estimator during the same cycle that frame 402 is processed in the second phase. Encoding of a frame is completed when the second phase and final encoding operations are completed, so after second phase motion estimation for frame 401 is completed at time 411, frame 401 has been fully encoded. Then, the motion estimator regularly performs the following steps in a cycle: phase one motion estimation for frame 404 (at time 412), scene change detection (at time 413), 3:2 pull-down detection (at time 414), and phase two motion estimation and final encoding for frame 402 (at time 415).

[0066] Two frames before the next I-frame 408 is fully encoded at time 418, at time 416 phase one for frame 409 is completed. During this cycle, phase two for frame 406 is completed, so it would be expected that phase one for frame 408 would be executed because of the two frame delay. However, frame 408 is an I-frame, and as such has no motion vectors, and therefore does not require phase one motion estimation. So, the frame after the I-frame, frame 409, is encoded at time 416. Additionally, since there are

no motion vectors for frame 408, scene change and 3:2 pull-down detections are not performed. At time 418, an extra frame is encoded, so at time 419, the two frame delay and the cycle return to normal.

[0067] Figure 5 is a timing diagram for a video sequence with repeated fields. Frames 501, 502, 503, 504, 505, 506, 507, and 508 are to be encoded in sequence. Here, repeated fields can be encoded into the same frame as the field they are repeated from. So, frame 504 has three fields, field 510 is a repeat of field 509. Similarly, frame 506 has three fields, field 512 is a repeat of field 511. When encoding three fields into one frame, there will be a time gain. For example, at time 513, when encoding frame 504, there is extra time because the field 510 does not need to be encoded again. This extra time can be used to improve picture quality by taking an average of the two essentially identical fields 509 and 510 for noise reduction or by doing motion estimation refinement. There is also extra time at time 514, when encoding frame 506. As shown here, the extra time gained because of the repeated field is less for frame 506 than for 504. It is understood that the amount of time gained is variable, and will differ.

[0068] In one embodiment, after two repeated fields are removed, at time 515, the first phase of the motion estimator needs to be executed twice to keep up with the advance set of motion vectors.

[0069] Figure 6 is a timing diagram for a video sequence with an I-frame in between two repeated fields. Frames 601, 602, 603, 604, 605, 606, 607, and 608 are to be encoded in sequence. Here, frames 601 and 606 have repeated fields, and frame 605 is an I-frame. Field 610 is a repeat of field 609, and is a top field, whereas field 612 is a repeat of field 611, and is a bottom field. In one embodiment, the encoder would be operating in a top-field-first condition. However, when there is a repeated field as with frame 601, the bottom field 613 of frame 602 will be encoded first, and the top field 614 second, and the encoder will be running in a bottom-field-first condition. Normally, another frame with a repeated field would intervene and return the process to encoding the top field first. I-frame 605 occurs before top-field-first encoding can be resumed. So, to remedy this problem, the encoder can simply encode the bottom field 615 of I-frame 605 first.

[0070] Figure 7 is a timing diagram for a video sequence with a scene change during a top-field-first situation. Frames 701, 702, 703, 704, 705, 706, 707, and 708 are to be

encoded in sequence. Figure 14 further illustrates the sequence running in a top-field-first situation. There is a scene change detected between frames 702 and 703. Ideally, then, frame 703 would be encoded as an I-frame. There are concerns about the speed of variable length encoding (VLE), and because there is low visual sensitivity before and after the scene change, the I-frame can be postponed until frame 705. Also, frames 702 and 703 can be encoded as P-frames without adverse effect.

[0071] Figure 8 is a timing diagram for a video sequence with a scene change during a bottom-field-first situation. Frames 801, 802, 803, 804, 805, 806, 807, and 808 are to be encoded in sequence. Frame 803 has a repeated field, and this causes the sequence to begin encoding bottom-field-first starting with frame 804. Further, there is a scene change detected between frames 804 and 805. This may cause an extra field 809, the bottom field of frame 804, to occur which cannot be encoded with frame 804, since frame 804 has already been encoded, and which cannot be encoded with frame 805, since frame 805 is a different scene. This can be remedied by replacing field 809 with the bottom field 810 of frame 805, and encoding frame 805 as a frame with a repeated field. The remaining fields can then be encoded as top-field-first.

[0072] Figure 9 illustrates another embodiment of an encoder. In this embodiment, the encoder is capable of encoding all three types of MPEG frames – I-frames, P-frames, and B-frames. However, it is understood that the following flow diagram represents the operation of only one specific embodiment, and that other embodiments may exist. This embodiment of an encoder uses many of the same steps and processes as the encoder described in Figure 1. It uses a two-phase motion estimation, scene change detection, and 3:2 pull-down detection. The process 900 encodes an entire GOP. The encoder operates in two stages – a start stage 901 and a process stage 902.

[0073] The start stage 901 includes initializing the encoder so that it can begin normal operation on the GOP. The encoder receives an input of video, and processes two frames in the first phase of motion estimation to provide the forward field motion vectors to complete the scene change detection and 3:2 pull-down detection operations later in encoding. First, the first frame of video is prefiltered in block 903. Then, the first phase of motion estimation is completed for the first frame in block 904. The first phase of motion estimation provides the field motion vectors – the motion vectors that relate the two fields of the same polarity, as explained above. In block 905, the second

frame of video is prefiltered, and in block 906, first phase motion estimation is performed on the second video frame.

[0074] Process stage 902 does the encoding for each GOP. After determining two sets of field motion vectors, the process stage begins in block 907, where scene change detection is performed to determine if there is a scene change between the I-frame and the following frame. In block 908, 3:2 pull-down detection is to check whether there is a field repetition after this I-frame. In blocks 909 and 910, scene change detection and 3:2 pull-down detection is performed for the frame following the I-frame. In block 911, the I-frame is encoded. In block 912, if the next to be coded frame is an I-frame, the process returns to block 907. The procedures in blocks 907-911 are performed when a new GOP is going to be encoded.

[0075] In one embodiment, if a scene change is found either in the frame after a predetermined I-frame, or two frames after this I-frame, then this I-frame may be encoded as a P-frame in order to save resources, since the full encoding of the I-frame will not be referenced if a new GOP will be started soon afterward. Further, if the frame immediately following the I-frame has a repeated field, as would be detected by the 3:2 pull-down detection, a repeated field flag can be set while encoding the I-frame in block 911. According to one embodiment, a repeated field flag in an MPEG encoded video bitstream indicates to a decoder that a repeated field exists and the decoder needs to compensate for that repeated field.

[0076] In block 912, if the next frame is a B or P frame, encoding continues with block 913. In block 913, the next frame is prefiltered. To have two sets of motion vectors in advance for the detections, the field motion vectors are determined in block 914 when the first phase of motion estimation is executed. In block 915, scene change detection is executed for the frame. If a scene change is detected, the encoder can start a new GOP in the next frame to reflect the fact that the video has a new scene. More detailed case studies of scene change detection can be found below. In block 916, 3:2 pull-down detection is performed to detect repeated fields for the next frame. If a repeated field is detected, the repeated field can be encoded with the previous frame. An encoder can eliminate a repeated field using a number of methods, including removing the field and inserting a reference to the field from which it was repeated, or averaging the two repeated fields to obtain higher quality video. In block 917, the P- or B-frame is

encoded by completing the encoding of the motion vectors using the second phase of motion estimation. Once the encoding of frames is completed in block 917, the process may begin again at block 912, until the GOP is finished.

[0077] When a scene change is detected, the encoder must determine what to do with the current frame and the following frames. The encoder could encode the current frame as an I-frame beginning a new GOP, but if the encoder considers the human visual system, there may be a better way to respond to a scene change. Since the sensitivity of human visual system drops before and after a scene change happens, the pictures close to a new scene can be coded in lower quality to save processing resources. Figures 10 through 13 illustrate several examples of situations in which a scene change is detected. The specifics of scene change detection are explained below.

[0078] Figure 10 illustrates a video sequence having a scene change after an I-frame and before a B-frame. In the video sequence 1000, the scene change occurs after I-frame 1001 at frame 1002, a B-frame. The video sequence consists of top fields 1004, 1006, 1008, 1010, 1012, 1014, and 1016, and bottom fields 1018, 1020, 1022, 1024, 1026, 1028, and 1030. Frame 1002 is comprised of fields 1010 and 1024. Further, sequence 1000 has set of motion vectors 1032 relating fields 1004 and 1008, set of motion vectors 1034 relating fields 1004 and 1006, set of motion vectors 1036 relating fields 1008 and 1012, set of motion vectors 1038 relating fields 1008 and 1010, set of motion vectors 1040 relating fields 1018 and 1022, set of motion vectors 1042 relating fields 1018 and 1020, set of motion vectors 1044 relating fields 1022 and 1026, and set of motion vectors 1046 relating fields 1022 and 1024.

[0079] When a scene change occurs immediately after an I-frame, it may be advantageous to code the I-frame as a P-frame, because an I-frame occupies considerably more space than a P-frame, and may not be very useful as a reference frame because of the scene change. The encoder may then encode frame 1001 as a P-frame, and because frame 1001 is now a P-frame, frame 1001 needs motion vectors. As a result, motion estimation must be performed, resulting in sets of motion vectors 1032 and 1040. The I-frame can be delayed to a later P-frame, here frame 1050 would become an I-frame, since the motion vectors for frame 1050 have not yet been calculated, and it will save processing time to use the motion vectors which had already been calculated for P-frame 1048. In addition, encoder can allocate fewer resources for encoding frames 1002 and

1048 due to the lack of sensitivity of the human visual system near a scene change, and save the resources for the other more important frames.

[0080] Figure 11 illustrates a video sequence having a scene change occurring two frames after an I-frame. A scene change is detected in video sequence 1100 at frame 1102. An I-frame was originally scheduled to occur at frame 1104, but for the same reasons as above, the encoder can delay the I-frame. When frame 1104 is converted from an I-frame to a P-frame, sets of motion vectors 1106 and 1108 must be determined. The I-frame may be delayed until P-frame 1110, and since no motion vectors have been determined for frame 1110, no computation will be wasted.

[0081] Figure 12 illustrates a video sequence having a scene change happening at a B-frame. Here, unlike the situation in Figure 10, the scene change occurs at a B-frame, but not immediately after an I-frame. In video sequence 1200, the scene change occurs at frame 1202. I-frame may be encoded at frame 1204, immediately after the scene change, since there is no recent I-frame. The next P-frame, frame 1204, can be converted to an I-frame, and since no motion vectors had been determined for frame 1204, no computation is wasted.

[0082] Figure 13 illustrates a video sequence having a scene change occurring at a P-frame. In video sequence 1300, the scene change occurs at frame 1302. Since motion vectors have already been determined for frame 1302, the encoder may choose to delay the encoding of a new I frame to frame 1308, the next P-frame.

[0083] When a repeated scene is detected using 3:2 pull-down detection, the encoder determines what to do with the current frame and the following frames. Figures 14 through 16 illustrate several examples of situations in which a repeated field is detected.

[0084] Figure 14 illustrates a video sequence having a repeated field in an I-frame. Video sequence 1400 comprises top fields 1402, 1404, 1406, and 1408, and bottom fields 1410, 1412, 1414, and 1416. I-frame 1418 comprises fields 1402, 1404, and 1410. Field 1404 is a repeated field from field 1402. Video sequence 1400 further has sets of motion vectors 1420, 1422, 1424, and 1426.

[0085] A 3:2 pull-down inverse can be performed to remove the repeated field 1404. When the repeated field 1404 is removed, and replaced with a reference to field 1402, the next frame 1428 will be encoded in a bottom-frame-first condition. Further, frame 1430 will be referencing to frame 1418 for motion estimation. Because the set of motion

vectors 1422 will no longer be useful to the encoder, set of motion vectors 1432 must be established relating field 1408 and field 1402. The encoder can then continue to operate as normal, in a bottom-field-first situation until next repeat field is detected.

[0086] Figure 15 illustrates a video sequence having a repeated field in a B-frame. Video sequence 1500 comprises top fields 1502, 1504, 1506, and 1508, and bottom fields 1510, 1512, 1514, and 1516. B-frame 1518 comprises fields 1504, 1506, and 1512. Field 1506 is a repeat of field 1504. Video sequence 1500 also has sets of motion vectors 1520, 1522, 1524, and 1526. The next frame in the sequence, frame 1528, will be encoded in the bottom-field-first situation.

[0087] Repeated field 1506 will be replaced with a reference to field 1504. Because set of motion vectors 1520, which field 1506 was using for encoding, are no longer needed, they can be removed. Field 1506 was referring to field 1502 for motion estimation, but now that field 1506 has been removed, field 1508 can refer to field 1502 using motion vector 1530. Rearranging the motion vectors in this manner allows the encoder to keep the correct timing.

[0088] Figure 16 illustrates a video sequence having a repeated field in a P-frame. Video sequence 1600 comprises top fields 1602, 1604, and 1606, and bottom fields 1608, 1610, and 1612. P-frame 1614 is comprised of fields 1602, 1604, and 1608. Field 1604 is a repeated field of field 1602. Because field 1604 will be removed and replaced with a reference to field 1602, set of motion vectors 1616 relating field 1604 and 1602 is no longer necessary. Instead, motion vector 1618 may be substituted, relating field 1606 to field 1602.

[0089] For any of the cases in Figures 14, 15, and 16, a bottom-field-first situation would be processed in the same manner.

[0090] For this embodiment of an encoder, the first phase motion estimation can be executed a few frames in advance for future use in scene change detection and 3:2 pull-down detection. However, because of variable length encoding (VLE), a condition in which a certain length of video does not necessarily occupy a constant amount of data storage, I-frame encoding requires extra time. To compensate for this, in one embodiment, motion estimation for future frames is not determined during I-frame encoding. Also, since, in one embodiment, the encoder needs to encode P-frames before B-frames, and as a result, there is a three frame delay for both I- and P-frame encoding.

[0091] For example, the encoder would begin by prefiltering a frame at time 0, and prefiltering another frame at time 1. At time 2, the encoder prefilters a third frame, and does first phase motion estimation for the first frame that was prefiltered at time 0. At time 3, the encoder prefilters a fourth frame, and performs first phase motion estimation for the second frame which was prefiltered at time 1. At time 4, the encoder prefilters a fifth frame, performs first phase motion estimation for the third frame prefiltered at time 2, performs scene change and 3:2 pull-down detection for the first frame, using motion vectors from the first phase motion estimation at time 3, and finished by encoding the frame, including the second phase motion estimation. At time 5, the entire cycle is repeated, and so on, until the next I-frame comes up in the video sequence.

[0092] Figure 17 is a block diagram of an encoder according to one embodiment. Video frames enter the system at point 1702. For the following description, it is assumed that the frame currently entering the encoder is frame k. At block 1704, the encoder checks whether the incoming frame k is scheduled to be encoded as an I-frame.

[0093] If frame k is an I-frame, processing moves on to block 1706, where the encoder sets variables is_new_scene and skip_detect to 0. In one embodiment, variables is_new_scene and skip_detect are flags used by an encoding scheme to instruct a decoder to properly decode a video bitstream. is_new_scene tells the encoder whether the current frame marks the beginning of a new scene, if it is equal to 0, then the current frame is not the beginning of a new scene, and if it is equal to 1, then the current frame is the beginning of a new scene. skip_detect is a variable which tells the encoder whether or not to perform the 3:2 pull-down and scene change detections, a value of 0 means that the detections should be performed, and a value of 1 means that they should be skipped. Further, in block 1706, the motion vector buffers for frames k+1 (the frame immediately following frame k) and k+2 are located. The process moves to block 1708, where if the frame is in a top-field-first situation, the process will move on to block 1710, whereas if the frame is not in a top field first situation, the process will move to block 1712, where the I-frame will be encoded, and the process will move back to point 1702.

[0094] At block 1710, scene change detection is performed for the frame k+1. If there is a scene change, the process moves on to 1714, where the current frame k, which is an I-frame will be changed to a P-frame, and new motion vectors will be determined

for the frame, as was explained in Figure 10. The process will then move on to block 1716, where the P-frame will be encoded, and the process will return to point 1702.

[0095] At block 1710, if there is no scene change, the process moves on to block 1718, where 3:2 pull-down detection is performed for the I-frame k. If a repeated field is detected, the process moves to block 1720, where the pull-down handler is executed for the necessary adjustment as was explained in Figure 14, and moves to block 1712, where the I-frame is encoded, and finally returns to point 1702.

[0096] At block 1718, if there is no repeated field, the process moves to block 1722, where scene change is performed for the next frame. If there is a scene change, the process continues to block 1724, where the scene change handler is called for the adjustment explained in Figure 11, and the process moves on to block 1716 for encoding, and finally back to point 1702.

[0097] At block 1722, if there is no scene change, the process continues to block 1726, where 3:2 pull-down detection is performed on the next frame. If there is a repeated field, the process continues to block 1728, where the pull-down handler is executed for the necessary adjustment explained in Figure 15, and then proceeds to block 1712, where the I-frame is encoded, and finally returns to point 1702.

[0098] If, in block 1704, frame k is not an I-frame, the process continues to block 1730. In block 1730, the first phase of motion estimation is performed for future frames, and skip_detect is set to 0 or 1. The process continues to block 1732, where if either is_new_scene or skip_detect are equal to 1, the process continues to block 1716, and the frame is encoded before returning to point 1702.

[0099] If, at block 1732, it is determined that both is_new_scene and skip_detect are equal to 0, then the process continues to block 1734. At block 1734, the encoder locates the first and second motion vector buffers for detection, and gets the picture type for the detection frame. The process then continues to block 1736, where it is determined whether the variable is_frame_gain is equal to 1 or 0. If is_frame_gain is equal to 1, then there is a pair of repeated fields being detected and the encoder gains one frame of time. The process continues to block 1738, where a scene change detection is performed.

[00100] If a scene change is detected in block 1738, the process moves to block 1740, where the scene change handler is run, the first phase of motion estimation for future frames is performed, and the skip_detect variable is set. The process then continues to

block 1742, where `is_frame_gain` is set to 0 to reset the indicator of frame gain, and finally the process returns to point 1702.

[00101] If at block 1738 it is determined that there is no scene change at frame `k`, the process continues to block 1744, where the first phase of motion estimation is performed for future frames, and the `skip_detect` variable is set to 0 or 1 based on whether there are enough sets of field motion vectors for detections to be performed. The process continues to block 1746, where if `skip_detect` is equal to 1, the process continues to block 1742, and back to point 1702. If, at block 1746, `skip_detect` is equal to 0, the process continues to block 1748. At block 1748, the next pair of sets of motion vectors and the picture coding type for the next frame are retrieved, and the process continues to block 1750.

[00102] At block 1750, a scene change detection is performed using the motion vector sets from block 1748. If a scene change is detected, the process continues to block 1752, where the scene change handler is called for the adjustment explained in Figures 12 and 13, and then the process continues to block 1742, and finally back to point 1702. If there is no scene change at block 1750, the process continues to block 1754, where 3:2 pull-down detection is executed. If there is a repeated field, the process continues to block 1756, where the pull-down handler is called for the necessary adjustment as explained in Figures 15 and 16, and then to block 1742, and finally back to point 1702. If there is no repeated field at block 1754, the process continues to block 1742, and finally to point 1702.

[00103] At block 1736, if the `is_frame_gain` variable is equal to 0, the process continues to block 1758, where a scene change detection is performed. If there is a scene change, the process continues to block 1760 where the scene change handler is called for the adjustment explained in Figures 12 and 13, and to block 1716, where the frame is encoded, and finally returns to point 1702. If there is no scene change detected in block 1758, the process continues to block 1762. At block 1762, the 3:2 pull-down detection is executed to determine if there is a repeated field. If there is a repeated field, the process continues to block 1764 where the pull-down handler is executed for the necessary adjustment explained in Figures 15 and 16, and on to block 1716 for frame encoding, and finally back to point 1702. If there is no repeated field at block 1762, the process continues to block 1716 for frame encoding, and back to point 1702.

[00104] As discussed above the encoders described selectively detect repeated fields using 3:2 pull-down detection. Figures 18a through 21 explain methods for detecting repeated fields using 3:2 pull-down detection according to one embodiment.

[00105] Figure 18a illustrates two video frames and sets of motion vectors relating the two video frames. Video frame 1805 comprises two fields, top field 1810 and bottom field 1815. Similarly, video frame 1820 similarly comprises two fields, top field 1825 and bottom field 1830. In this embodiment, video frames 1805 and 1820 are interlaced video frames, meaning that two fields make up each frame. However, it is understood that any configuration of video frames may be used.

[00106] Set of motion vectors 1835, 1840, 1845, 1850 and 1855 relate video frames 1805 and 1820. As explained above, a motion vector relates the motion of one block or region of a field to another field. Therefore, there are typically several motion vectors that relate two fields. Here, the arrows representing sets of motion vectors 1835, 1840, 1845, 1850, and 1855 may actually represent several motion vectors.

[00107] Set of motion vectors 1835 describes the relationship between top field 1810 and top field 1825. Set of motion vectors 1840 describes the relationship between top field 1810 and bottom field 1830. Set of motion vectors 1845 describes the relationship between first video frame 1805, and second video frame 1820. Set of motion vectors 1850 describes the relationship between bottom field 1815 and top field 1825. Set of motion vectors 1855 describes the relationship between bottom field 1815 and bottom field 1830.

[00108] Since top field 1810 and top field 1825 are both the top fields in a frame, they are said to be of the same polarity. Likewise, bottom field 1815 and bottom field 1830 are of the same polarity, since they are both bottom fields. Further, the sets of motion vectors 1835 and 1855 are known as field motion vectors, since they relate two fields of the same polarity.

[00109] When encoding, it is possible to use motion vectors to determine whether a repeated field exists. For example, if field 1825 were a repeat of field 1810, then theoretically, all members of the set of motion vectors 1835 would have a magnitude of zero, since there would be no changes to track between the two fields. However, there is always some noise in any video system and some or all of the members of set motion vector 1835 may have some non-zero magnitude. However, if field 1825 is a repeat of

field 1810, the sum of the magnitudes of the members of the set of motion vectors 1835 could be much less than will be the sum of the magnitudes of the members of the set of motion vectors 1855 relating fields 1830 and 1815, which are not repeated.

[00110] The following describes a process to detect repeated fields in a general manner, with more specific examples following. To find repeated fields, set of motion vectors 1855 and 1835 can be compared. A ratio of the sum of the magnitudes the members of set of motion vectors 1835 and the sum of the magnitudes the members of set of motion vectors 1855 can be compared to a threshold value. The threshold value accounts for noise, and can be a heuristically determined value. The detail will be explained later. If field 1825 is found to be a repeated field of field 1810, then it is only necessary to encode field 1825 by referring to the earlier field 1810. Additionally, one frame could be encoded with three fields, including the repeated field, and could further include references to account for the proper timing. Thusly, the encoder may save the bits that would be used to describe the motion vectors and the residual errors and the processing that would be necessary to reconstruct field 1825 and instead include only a reference to the earlier field 1810. Further, little additional processing has to be done using this method, since these motion vectors have to be calculated as part of the encoding process anyway.

[00111] To determine a repeated field, an encoder using motion vectors to execute 3:2 pull-down detection does not need to know the noise level in the system. Current methods of detecting repeated fields need to determine a noise level to detect whether there is a repeated field. Because motion vectors alone are enough to determine whether a repeated field exists, the additional computations of determining noise levels can be avoided.

[00112] As a result, if the field is repeated, it can be removed from the encoding process and the sets of motion vectors 1840, 1845 and 1850 need not be calculated. Consequently, a large amount of processing time and storage space may be saved.

[00113] Figure 18b illustrates a sequence of frames operating in a top-field-first condition. In a top-field-first condition, the top field of a frame is display before the bottom field. Sequence of frames 1860 has frame 1861 having a top field 1862 and a bottom field 1863. Since the encoder is operating in a top-field-first condition, the top field 1862 will come before the bottom field 1863. Top fields 1864 and 1865 follow

frame 1861. Set of motion vectors 1866 is a set of motion vectors between fields 1862 and 1864, which may also be referred to as $V_{0,1}$. Similarly, set of motion vectors 1867, which is between fields 1864 and 1865, may be referred to as $V_{1,2}$.

[00114] Figure 18c illustrates a sequence of frames with a repeated field in a top-field-first condition. Sequence of frames 1870 has frame 1871 having a top field 1872, bottom field 1873, and repeated top field 1874. Following frame 1871 are bottom field 1875 and top field 1876. Set of motion vectors 1877 relates top field 1872 and repeated field 1874, and may also be referred to as $V_{0,1}$. Similarly, set of motion vectors 1878 relates bottom field 1873 and bottom field 1875, and may be referred to as $\Lambda_{0,1}$, the Λ indicating that it is a set of motion vectors relating a pair of fields of the opposite polarity as the set of motion vectors represented by V . Also, set of motion vectors 1879 relates top field 1874 and top field 1876, and may also be referred to as $V_{1,2}$.

[00115] Figure 18d illustrates a sequence of frames operating in a bottom-field-first condition. In a bottom-field-first condition, the bottom field of a frame is display before the top field. Sequence of frames 1880 has frame 1881 having a top field 1882 and a bottom field 1883. Since the encoder is operating in a bottom-field-first condition, the bottom field 1883 will come before the top field 1882. Bottom fields 1884 and 1885 follow frame 1881. Set of motion vectors 1886 is a set of motion vectors between fields 1882 and 1884, which may also be referred to as $V_{0,1}$. Similarly, set of motion vectors 1887, which is between fields 1884 and 1885, may be referred to as $V_{1,2}$.

[00116] Figure 18e illustrates a sequence of frames with a repeated field in a bottom-field-first condition. Sequence of frames 1890 has frame 1891 having a top field 1892, bottom field 1893, and repeated bottom field 1894. Following frame 1891 are top field 1895 and bottom field 1896. Set of motion vectors 1897 relates bottom field 1893 and repeated field 1894, and may also be referred to as $V_{0,1}$. Similarly, set of motion vectors 1898 relates top field 1892 and top field 1895, and may be referred to as $\Lambda_{0,1}$, the Λ indicating that it is a set of motion vectors relating a pair of fields of the opposite polarity as the set of motion vectors represented by V . Also, set of motion vectors 1899 relates bottom field 1894 and bottom field 1896, and may also be referred to as $V_{1,2}$.

[00117] The detection of repeated fields can be represented by the following equations. In this first equation, repeated fields can be detected in a video sequence containing I and P frames:

$$\text{If } \frac{\sum |V_{0,1}|_c + \varepsilon}{\sum |V_{1,2}|_c + \varepsilon} < \tau \text{ and } \frac{\sum |\wedge_{0,1}|_c + \varepsilon}{\sum |V_{0,1}|_c + \varepsilon} > \frac{1}{\tau},$$

Then field t+1 is a repeated field from field t for top-field first cases, or field b+1 is a repeated field from field b for bottom field cases. Here, t and b can be the top and bottom fields of a frame at time 0. $|_c$ means that the absolute values for all components of the vectors are used. ε is a small positive number to avoid false detection and division by zero. $V_{i,j}$ represents the set of motion vectors between the fields t+i and t+j or between the fields b+i and b+j. $\wedge_{i,j}$ represents the motion vectors between the fields having the opposite polarity from the fields represented by $V_{i,j}$, or, in other words, if the fields represented by $V_{i,j}$ are the top fields, then the fields of opposite polarity are the bottom fields, and vice versa.. τ is the predetermined threshold.

[00118] Figures 19a, 19b, 19c, 19d, 19e, and 19f illustrate a sequence of frames having repeated fields according to one embodiment. The following equations may be used to detect repeated fields where there are B frames in a video stream. In the following equations, the variables are the same as above, but also include two thresholds τ_1 and τ_2 , where τ_1 should be smaller than 1, and τ_2 should be larger than 1, or about 2, and k, where k is the frame distance between the reference field and the target field, in the following illustrations, k=2. Further, when referring to a set of vectors between two fields, for example, the notation $V_{t0 \rightarrow t1}$ represents the set of motion vectors between a first top field (field t0) and a second top field (field t1), the field t1 in the frame immediately proceeding the frame having the field t0. Likewise, the notation $V_{t0 \rightarrow t2}$ refers to a set of motion vectors between a field t0, and a field t2, the field t2 coming two frames after the field t0. A field b0 would refer to the bottom field of the frame of field t0.

[00119] The following equation can be used to determine if there is a repeated field in a situation in which a video sequence is operating top-field first, and the current frame is an I frame:

$$\text{If } \frac{\sum |V_{t0 \rightarrow t1}|_c}{\sum |V_{t0 \rightarrow t2}|_c} < \tau_1 \text{ and } \frac{\sum |V_{b0 \rightarrow b1}|_c}{\sum |V_{t0 \rightarrow t1}|_c} < \tau_2 \text{ then field t1 is repeated}$$

[00120] Such a situation is illustrated in Figure 19a Video sequence 1900 has a current frame with a repeated field 1901, top fields 1902, 1903, 1904, and 1905, and bottom fields 1906, 1907, 1908, and 1909. Fields 1902 and 1903 are repeated, and frame Application

1901 is made up of fields 1902, 1903 and 1906. In the equations, fields 1902, 1903, 1904, and 1905 correspond to fields t0, t1, t2, and t3, respectively. Similarly, fields 1906, 1907, 1908, and 1909 correspond to fields b0, b1, b2, and b3, respectively. Since fields 1903 and 1907 are originally scheduled as a B-frame, which can not be used as a reference frame, top field 1904 has motion vectors referring to field 1902 rather than field 1903.

[00121] If the above equation is true, then field 1903 is a repeat of field 1902, and it can be encoded as such. Further, the encoder should begin encoding bottom-field-first, starting with field 1907. Thus, the frame following frame 1901 will be comprised of fields 1904 and 1907.

[00122] The following equation can be used to determine if there is a repeated field in a situation in which a video sequence is operating top-field first, and the current frame is a B frame:

$$\text{if } \frac{|\sum |V_{t0 \rightarrow t1}|_c - \sum |V_{t0 \rightarrow t2}|_c|}{\sum |V_{t0 \rightarrow t1}|_c} < \tau_1, \frac{|\sum |V_{b0 \rightarrow b1}|_c - \sum |V_{b0 \rightarrow b2}|_c|}{|\sum |V_{t0 \rightarrow t1}|_c - \sum |V_{t0 \rightarrow t2}|_c|} > \tau_2, \text{ and}$$

$$\frac{\sum_{k=1}^N |V_{t0 \rightarrow t1}|_c - \sum_{k=1}^N |V_{t0 \rightarrow t2}|_c|}{\sum_{k=1}^N |V_{t0 \rightarrow t1}|_c} < \tau', \text{ then field t2 is repeated}$$

[00123] Such a situation is illustrated in Figure 19b. Video sequence 1910 has a current frame 1911 with a repeated field, top fields 1912, 1913, 1914, and 1915, and bottom fields 1916, 1917, 1918, and 1919. Fields 1912, 1913, 1914, and 1915 correspond to fields t0, t1, t2, and t3, respectively. Similarly, fields 1916, 1917, 1918, and 1919 correspond to fields b0, b1, b2, and b3. Fields 1914 and 1913 are repeated, and frame 1911 is made up of fields 1913, 1914 and 1917. Since fields 1913 and 1917 are originally scheduled as a B-frame, top field 1914 has motion vectors referring to field 1912 rather than field 1913.

[00124] If the above equation is true, then field 1914 is a repeat of field 1913, and it can be encoded as such. Further, the encoder should begin encoding bottom-field-first, starting with field 1918.

[00125] The following equation can be used to determine if there is a repeated field in a situation in which a video sequence is operating top-field first, and the current frame is a P frame:

$$\text{if } \frac{\sum |V_{t2 \rightarrow t3}|_c}{\frac{1}{k} \sum |V_{t0 \rightarrow t2}|_c} < \tau_1 \text{ and } \frac{\sum |V_{t0 \rightarrow t1}|_c + \varepsilon}{\sum |V_{t1 \rightarrow t2}|_c + \varepsilon} > \tau_1, \text{ then field } t3 \text{ is repeated}$$

[00126] Such a situation is illustrated in Figure 19c. Video sequence 1920 has a current frame 1921 with a repeated field, top fields 1922, 1923, 1924, and 1925, and bottom fields 1926, 1927, 1928, and 1929. Fields 1922, 1923, 1924, and 1925 correspond to fields t0, t1, t2, and t3 respectively. Similarly, fields 1926, 1927, 1928, and 1929 correspond to fields b0, b1, b2, and b3 respectively. Fields 1924 and 1925 are repeated, and frame 1921 is made up of fields 1924, 1925 and 1928. Because field 1925 is a repeat of field 1924, there is no need to create a set of motion vectors relating fields 1925 and 1924 other than the field motion vectors, and the encoder need only make a note that fields 1925 and 1924 are the same.

[00127] If the above equation is true, then field 1925 is a repeat of field 1924, and it can be encoded as such. Further, the encoder should begin encoding bottom-field-first, starting with field 1929.

[00128] The following equation can be used to determine if there is a repeated field in a situation in which a video sequence is operating bottom-field first, and the current frame is an I frame:

$$\text{if } \frac{\sum |V_{b0 \rightarrow b1}|_c}{\sum |V_{b0 \rightarrow b2}|_c} < \tau_1 \text{ and } \frac{\sum |V_{t0 \rightarrow t1}|_c}{\sum |V_{b0 \rightarrow b1}|_c} > \tau_2 \text{ then field } b1 \text{ is repeated}$$

[00129] Such a situation is illustrated in Figure 19d. Video sequence 1930 has a current frame 1931 with a repeated field, top fields 1932, 1933, 1934, and 1935, and bottom fields 1936, 1937, 1938, and 1939. Fields 1932, 1933, 1934, and 1935 correspond to fields t0, t1, t2, and t3, respectively. Similarly, fields 1936, 1937, 1938, and 1939 correspond to fields b0, b1, b2, and b3, respectively. Fields 1936 and 1937 are repeated, and frame 1931 is made up of fields 1932, 1936 and 1937. Because field 1937 is a repeat of field 1936, there is no need to create a set of motion vectors relating fields 1937 and 1936 other than the field motion vectors, but the encoder need only make a note that fields 1937 and 1936 are the same.

[00130] If the above equation is true, then field 1937 is a repeat of field 1936, and it can be encoded as such. Further, the encoder should begin encoding top-field-first, starting with field 1933.

[00131] The following equation can be used to determine if there is a repeated field in a situation in which a video sequence is operating bottom-field first, and the current frame is a B frame:

$$\text{if } \frac{|\sum |V_{b0 \rightarrow b1}|_c - \sum |V_{b0 \rightarrow b2}|_c|}{\sum |V_{b0 \rightarrow b1}|_c} < \tau_1, \frac{|\sum |V_{t0 \rightarrow t1}|_c - \sum |V_{t0 \rightarrow t2}|_c|}{|\sum |V_{b0 \rightarrow b1}|_c - \sum |V_{b0 \rightarrow b2}|_c|} > \tau_2 \text{ and}$$

$$\sum |V_{b0 \rightarrow b2}|_c < \sum |V_{t0 \rightarrow t2}|_c \text{ then field b2 is repeated}$$

[00132] Such a situation is illustrated in Figure 19e. Video sequence 1940 has a current frame 1941 with a repeated field, top fields 1942, 1943, 1944, and 1945, and bottom fields 1946, 1947, 1948, and 1949. Fields 1942, 1943, 1944, and 1945 correspond to fields t0, t1, t2, and t3 respectively. Fields 1946, 1947, 1948, and 1949 correspond to fields b0, b1, b2, and b3 respectively. Fields 1948 and 1947 are repeated, and frame 1941 is made up of fields 1943, 1947 and 1948. Because field 1948 is a repeat of field 1947, the encoder need only make a note that fields 1948 and 1947 are the same.

[00133] If the above equation is true, then field 1948 is a repeat of field 1947, and it can be encoded as such. Further, the encoder should begin encoding top-field-first, starting with field 1944.

[00134] The following equation can be used to determine if there is a repeated field in a situation in which a video sequence is operating bottom-field first, and the current frame is a P frame:

$$\text{if } \frac{\sum |V_{b2 \rightarrow b3}|_c}{\frac{1}{k} \sum |V_{b0 \rightarrow b2}|_c} < \tau_1 \text{ and } \frac{\sum |V_{t2 \rightarrow t3}|_c}{\sum |V_{b2 \rightarrow b3}|_c} > \tau_2 \text{ then field b3 is repeated}$$

[00135] Such a situation is illustrated in Figure 19f. Video sequence 1950 has a current frame 1951 with a repeated field, top fields 1952, 1953, 1954, and 1955, and bottom fields 1956, 1957, 1958, and 1959. Fields 1952, 1953, 1954, and 1955 correspond to fields t0, t1, t2, and t3. Similarly, fields 1956, 1957, 1958, and 1959 correspond to fields b0, b1, b2, and b3. Fields 1958 and 1959 are repeated, and frame 1951 is made up of fields 1954, 1958 and 1959. Because field 1959 is a repeat of field 1958, there is no need to create a set of motion vectors relating fields 1959 and 1958 other than the field motion vectors, but the encoder need only make a note that fields 1959 and 1958 are the same.

[00136] If the above equation is true, then field 1959 is a repeat of field 1958, and it can be encoded as such. Further, the encoder should begin encoding top-field-first, starting with field 1955.

[00137] Figure 20 illustrates two frames and their associated motion vectors according to one embodiment. Video frame 2005 comprises top field 2010 and bottom field 2015. Video frame 2020 comprises top field 2025 and bottom field 2030. Field 2010 has associated motion vectors 2035 relating field 2010 to a previous reference field with the same polarity. Similarly, field 2015 has motion vectors 2040 also relating the field to a previous reference field with the same polarity. Field 2025 has motion vectors 2045 relating field 2025 to field 2010. Finally, field 2030 has motion vectors 2050 relating field 2030 to field 2015.

[00138] Motion vectors 2035, 2040, 2045 and 2050 represent the movement of blocks of fields 2010, 2015, 2025 and 2030. Each of the fields is divided into blocks, each block comprising a certain number of pixels. The movement of a block from field to field is tracked by the motion vectors.

[00139] Field 2025 is a repeated field of field 2010. This can be determined because of the relatively small magnitude and number of motion vectors 2045 as compared to the number of and magnitude of motion vectors 2050. Because there are relatively few motion vectors 2045, this indicates that the blocks of field 2010 have not moved much relative to the blocks of field 2025 any more than can be accountable to noise. Thus, motion vectors 2045 may be used to determine whether or not field 2025 is a repeat of field 2010. Further, as above, in comparing motion vectors 2050 to motion vectors 2045, it can be determined whether field 2025 is either repeated or whether the whole frame 2020 is the same as the previous frame 2005) because there is a still image.

[00140] Figure 21 is a flow diagram illustrating the process of detecting repeated fields according to one embodiment. This process is also known as 3:2 pull-down detection. At block 2105, a video device receives a first frame and a second frame. In one embodiment, each frame is interlaced, that is each frame is made up of two or more separate images or fields. A typical interlacing scheme has two fields for each frame, a first field and a second field, typically the first field being a top field and the second field being a bottom field, each field having alternating horizontal lines. At block 2110, a motion estimator determines a first set of motion vectors. Here, the first set of motion

vectors is between the first field of the first frame and the first field of the second frame. At block 2115, a second set of motion vectors is determined between the second field of the first frame and the second field of the second frame. At block 2120, these field motion vectors are used to determine whether one of the fields in the second frame is substantially similar to the corresponding field in the first frame. The specific manner for determining the repeated fields is detailed in Figures 19a, 19b, 19c, 19d, 19e, and 19f. Generally, the field motion vectors can be used to determine this because if a motion vector is determined between two identical fields, then the magnitude of the resulting motion vector will theoretically be zero. However, in real-world applications there is always some noise and some difference between the fields. If one of the two sets of motion vectors has a much smaller magnitude than the other, it can be said that there is a repeated field. Since motion vectors have to be determined as part of the encoding process anyway, efficiency can be increased by using those motion vectors to determine where repeated fields are, and then those repeated fields need not be physically encoded, but rather can use a reference to the earlier field from which they were repeated.

[00141] Figures 22a through 24 explain a method for detecting scene changes in a video sequence according to one embodiment.

[00142] Figures 22a, 22b, and 22c illustrate a sequence of frames containing a scene change according to one embodiment. A scene change occurs in a video sequence where the image in the video transitions from one scene to another distinguishably distinct scene. If an encoder knows where a scene change is, the encoder can begin a new Group of Pictures (GOP) with the new scene. Current methods for detecting a scene change require burdensome amounts of computation, as well as long delays, and therefore cannot be encoded real time using many current encoders.

[00143] According to one embodiment of the present invention, a video encoder can detect scene changes using sets of motion vectors which must be estimated as part of the normal encoding process. The encoder may use two sets of motion vectors, one set relating the top field of a first frame and the top field of a second frame, and another set relating the bottom field of a first frame and the bottom field of a second frame. Because the encoder can detect a scene change using these two sets of motion vectors, if a scene change is found, the estimation of remaining three sets of motion vectors (as explained with respect to Figure 18) and the mode decision for determining the final motion

vectors, need no longer be processed, as the encoder may encode the current frame as an I frame beginning a new GOP. Thus, the encoder uses less resources than previous approaches to detect the scene change, and once the scene change is detected, more computational load can be avoided such as the mode decision for determining the best motion vector from five candidates for each corresponding data block.

[00144] In one embodiment, the following three equations determine whether a scene change has happened following I-, B-, and P-frames. The calculations for top-field-first and for bottom-field-first are the same, so the top-field-first situation is shown below. If the encoder is running in bottom-field-first, the scene change calculation can be performed by simply replacing the references in the equations to top frames with references to bottom frames, and vice versa. The variables are the same as those explained above in Figures 19a through 19f, with the addition of num_mblock, which refers to the number of macroblocks in a frame. The threshold is used to avoid false detection due to small motion, field/frame repetition, or a main object having a large movement.

[00145] These equations determine whether a frame following an I-frame in a top-field-first situation is the site of a scene change:

$$\text{if } \frac{\sum |V_{t0 \rightarrow t1}|_c + \epsilon}{|\sum |V_{t0 \rightarrow t1}|_c - \sum |V_{t0 \rightarrow t2}|_c| + \epsilon} > \tau_1, \text{ and } \frac{\sum |V_{b0 \rightarrow b1}|_c + \epsilon}{|\sum |V_{b0 \rightarrow b1}|_c - \sum |V_{b0 \rightarrow b2}|_c| + \epsilon} > \tau_1, \text{ and } \sum |V_{t0 \rightarrow t1}|_c > \tau_2 * \text{num_mblock} \text{ then scene change at frame } t1/b1$$

This situation is illustrated in Figure 22a. Video sequence 2200 has top fields 2201, 2202, and 2203, and bottom fields 2204, 2205, and 2206. In the equations, fields 2201, 2202, and 2203 are referred to as fields t0, t1, and t2, respectively. Likewise, fields 2204, 2205, and 2206 are referred to as fields b0, b1, and b2 respectively. Set of motion vectors 2207 relates field 2203 to field 2201, set of motion vectors 2208 relates field 2202 to field 2201, set of motion vectors 2209 relates field 2206 to field 2204, and set of motion vectors 2210 relates field 2205 to field 2204. Here, if all of the above equations are satisfied, then a scene change happens at the frame comprising fields 2202 and 2205.

[00146] These equations determine whether a frame following an B-frame in a top-field-first situation is the site of a scene change:

$$\text{if } \frac{\sum |V_{t0 \rightarrow t2}|_c + \varepsilon}{\sum |V_{t0 \rightarrow t1}|_c + \varepsilon} > \tau_1, \frac{\sum |V_{b0 \rightarrow b2}|_c + \varepsilon}{\sum |V_{b0 \rightarrow b1}|_c + \varepsilon} > \tau_1 \text{ and } \sum |V_{t0 \rightarrow t2}|_c > \tau_2 * \text{num_mblock} \text{ then}$$

scene change at t2/b2

This situation is illustrated in Figure 22b. Video sequence 2220 has top fields 2221, 2222, and 2223, and bottom fields 2224, 2225, and 2226. In the equations, fields 2221, 2222, and 2223 are referred to as fields t0, t1, and t2, respectively. Likewise, fields 2224, 2225, and 2226 are referred to as fields b0, b1, and b2, respectively. Set of motion vectors 2227 relates field 2223 to field 2221, set of motion vectors 2228 relates field 2222 to field 2221, set of motion vectors 2229 relates field 2226 to field 2224, and set of motion vectors 2230 relates field 2225 to field 2234. Here, if all of the above equations are satisfied, then a scene change happens at the frame comprising fields 2223 and 2226.

[00147] These equations determine whether a frame following an P-frame in a top-field-first situation is the site of a scene change:

$$\text{if } \frac{\sum |V_{t2 \rightarrow t3}|_c + \varepsilon}{\sum |V_{t0 \rightarrow t2}|_c + \varepsilon} > \tau_1, \frac{\sum |V_{b2 \rightarrow b3}|_c + \varepsilon}{\sum |V_{b0 \rightarrow b2}|_c + \varepsilon} > \tau_1 \text{ and } \sum |V_{t2 \rightarrow t3}|_c > \tau_2 * \text{num_mblock} \text{ then}$$

scene change at t3/b3

[00148] This situation is illustrated in Figure 22c. Video sequence 2240 has top fields 2241, 2242, 2243, and 2244, and bottom fields 2245, 2246, 2247, and 2248. In the equations, fields 2241, 2242, 2243, and 2244 are referred to as fields t0, t1, t2, and t3, respectively. Likewise, fields 2245, 2246, 2247, and 2248 are referred to as fields b0, b1, b2, and b3, respectively. Set of motion vectors 2249 relates field 2243 to field 2241, set of motion vectors 2250 relates field 2244 to field 2243, set of motion vectors 2251 relates field 2247 to field 2245, and set of motion vectors 2252 relates field 2248 to field 2247. Here, if all of the above equations are satisfied, then a scene change happens at the frame comprising fields 2244 and 2248..

[00149] Figure 22d illustrates an interlaced video sequence having a scene change. Video sequence 2260 has top fields 2261, 2262, and 2263, and bottom fields 2264, 2265, and 2266. Set of motion vectors 2267 relates fields 2261 and 2262, set of motion vectors 2268 relates fields 2262 and 2263, set of motion vectors 2269 relates fields 2264 and 2265, and set of motion vectors 2270 relates fields 2265 and 2266. According to one embodiment, a scene change can be found in this sequence using the following equations:

$$\text{If } \frac{\sum |V_{t0 \rightarrow t1}|_c}{\sum |V_{t1 \rightarrow t2}|_c} > \tau_1 \text{ and } \frac{\sum |V_{b0 \rightarrow b1}|_c}{\sum |V_{b1 \rightarrow b2}|_c} > \tau_1 \text{ and } \sum |V_{t0 \rightarrow t1}|_c > (\tau_2 * \text{num_mblock}) \text{ then}$$

scene change at frame t1/b1.

[00150] The above equations use the same variables as the equations in Figures 22a, 22b, and 22c. Here, fields 2261, 2262, and 2263 correspond to fields t0, t1, and t2 respectively. Likewise, fields 2264, 2265, and 2266 correspond to fields b0, b1, and b2, respectively. If all of the above equations are true, then there is a scene change at the frame containing fields 2262 and 2265.

[00151] Figure 22e illustrates a progressive video sequence having a scene change. In a progressive video sequence, there are no fields, only video frames. Video sequence 2280 has frames 2281, 2282, and 2283. Set of motion vectors 2284 relates fields 2281 and 2282, and set of motion vectors 2285 relates fields 2282 and 2283. According to one embodiment, a scene change can be found using the following equations:

$$\text{If } \frac{\sum |V_{f0 \rightarrow f1}|_c + \epsilon}{\sum |V_{f1 \rightarrow f2}|_c + \epsilon} > \tau_1 \text{ and } \sum |V_{f0 \rightarrow f1}|_c > (\tau_2 * \text{num_mblock}) \text{ then scene change at}$$

frame f1.

[00152] The above equations use the same variables as the equations in Figures 22a, 22b, and 22c, with the addition of the variables f0, f1, and f2. Frame f1 corresponds to frame 2281, frame f2 corresponds to frame 2282, and frame f3 corresponds to frame 2283. If all of the above equations are true, then there is a scene change at frame 2282.

[00153] Figure 23 illustrates sets of motion vectors in two frames in a video sequence. Frame 2302 is immediately preceded by frame 2304. Frame 2302 is comprised of top field 2306 and bottom field 2308, and frame 2304 is comprised of top field 2310 and bottom field 2312. Motion vectors 2314 illustrate the magnitude and direction of blocks of field 2306 in relation to a reference frame immediately preceding frame 2302. Likewise, motion vectors 2316 illustrate the magnitude and direction of blocks of field 2308 in relation to a reference frame immediately preceding frame 2302. Motion vectors 2314 and 2316 are relatively small in magnitude. Thus, frame 2302 belongs to the same scene as the frame immediately preceding it.

[00154] However, examining the motion vectors 2318 and 2320 of fields 2310 and 2312, respectively, reveals that these motion vectors have magnitudes that are much larger and directions that are much more random than the motion vectors 2314 and 2316

of fields 2306 and 2308. Because motion vectors indicate the motion of blocks of one frame related to another, when there are very large and very random motion vectors for one frame, it can be concluded that that frame is not very similar to the frame from which it depends. Therefore, it can be said that there is a scene change in a frame which has motion vectors having large magnitude compared to the frame from which the current frame refers.

[00155] Figure 24 is a flow diagram generally illustrating one embodiment of a process described above for determining whether there is a scene change. At block 2402, the motion vectors are determined for the fields of the same polarity between the current frame and the frame to which the current frame refers. At block 2404, the motion vectors for the current frame are compared to the motion vectors of the previous frame. At block 2406, if it is determined that the ratio of the magnitudes for the total sets of motion vectors of the current frame and the previous frame are greater than a threshold and the magnitudes of the motion vectors for the current frame are relatively large, then a scene change is said to occur at the current frame.

[00156] The invention has been described in conjunction with the several embodiments. It is evident that numerous alternatives, modifications, variations, and uses will be apparent to one skilled in the art in light of the foregoing description.